

Alarm	P.7-2	Checking Memos.....	P.7-11
Registering Alarm.....	P.7-2	Editing Memo.....	P.7-12
Turning Alarm OFF.....	P.7-2	Deleting Memo.....	P.7-12
Editing Alarm.....	P.7-2	Voice Recorder	P.7-12
Deleting Alarm.....	P.7-3	Recording Voice.....	P.7-12
Stopping Alarm Sound.....	P.7-3	Setting Save Location for Voice.....	P.7-12
Timer	P.7-3	Playing Voice.....	P.7-13
Using Timer.....	P.7-3	Deleting Voice.....	P.7-13
Stop Watch	P.7-4	Viewing Voice Details.....	P.7-13
Using Stop Watch.....	P.7-4	Calculator	P.7-14
Infrared	P.7-4	Using Calculator.....	P.7-14
Receiving Data.....	P.7-4	Converter	P.7-15
Sending Data.....	P.7-5	Converter Window.....	P.7-15
Disaster	P.7-6	Using Converter.....	P.7-15
Urgent News.....	P.7-6	あんしんバックアップ (Anshin Backup)	P.7-16
Registering Safety Information (Disaster Message Board).....	P.7-6	Login with another SoftBank Account	P.7-17
Sending Voice Message (Disaster Voice Messaging).....	P.7-7	Checking Save/Restore History.....	P.7-17
Playing Received Voice Message (Disaster Voice Messaging).....	P.7-8	Checking Help in あんしんバックアップ (Anshin Backup).....	P.7-17
Calendar	P.7-9	Saving Data.....	P.7-18
Viewing Calendar.....	P.7-9	Restoring Data.....	P.7-18
Registering Schedule.....	P.7-9	Saving Data Regularly and Automatically	P.7-19
Viewing Schedule List.....	P.7-10	Reloading Phone Book Data Saved to Server in Case of Handset Upgrade/ Replacement.....	P.7-20
Checking Schedule.....	P.7-10	Deleting Saved Data.....	P.7-20
Editing Schedule.....	P.7-10	Notification List	P.7-21
Deleting Schedule.....	P.7-11	Application	P.7-22
Notepad	P.7-11		
Creating Memos.....	P.7-11		

Alarm

You are notified by alarm at the specified time.


■ Registering Alarm

Up to twenty alarms can be added.

- After Alarm is set, "🌐" appears in Status Bar.

1 In Standby,  → "Alarm" → "Alarm" →  (Menu) → "Add"

2 Select each item

Item	Operation/Description
Alarm set time	Enter start time for Alarm.
Repeat	Select whether to repeat Alarm. To select "Specify day": Check days of the week (☑) to specify →  (Done)
Snooze settings	Select Snooze interval. When Snooze is set, Alarm goes off repeatedly at the specified interval after Alarm stops ringing.
Label	Enter Alarm name
Prioritize alarm	Set whether to play alarm in Manner mode. Check/Uncheck "Prioritize alarm" (☑)/(☐)

3  (Set)



Alarm is registered.

■ Turning Alarm OFF



1 In Standby,  → "Alarm" → "Alarm" → Uncheck Alarm (☐) to turn OFF
Alarm is turned OFF.

■ Editing Alarm




1 In Standby,  → "Alarm" → "Alarm" → Select Alarm to edit

2  (Edit) → Enter each item →  (Set)
Editing Alarm is completed.









Deleting Alarm

- 1 In Standby,  → "Alarm" → "Alarm" → Select Alarm to delete
- 2  (Menu) → "Delete" → "Yes"
Alarm is deleted.

Stopping Alarm Sound

- 1 Press any key after Alarm goes off
Alarm sound is stopped.
 - To cancel Snooze, // → "Yes."

Using Timer

- 1 In Standby,  → "Alarm" → "Count Down Timer"
Count Down Timer window appears.
- 2  (Edit) → Specify time →  (Done)
 - To have the timer go off even in Manner Mode,  (Settings) → Check "Prioritize timer" ()
- 3  (Start)
The timer starts counting down.
 - To stop the timer counting down, press  (Stop). Press  (Start) again to have the timer restart counting down.
 - To reset the timer, press  (Reset) while the timer is counting down or counting down is stopped.





Stop Watch

■ Using Stop Watch

1 In Standby,  → "Alarm" → "Stop Watch"
Stop Watch window appears.

2  (Start)

Stop Watch starts measuring.

- To stop Stop Watch, press  (Stop) while Stop Watch is measuring. Press  (Start) again to have Stop Watch restart measuring.
- To record lap time and split time, press  (LAP) while Stop Watch is measuring.
- To reset the measurement result, press  (Reset).

Infrared

Exchange data (profile, Phone Book entries, etc.) with other devices such as mobile phones using infrared. With handset and other device close together, align their infrared ports in a straight line.

- Operations may differ depending on the type of data being sent/received.

CAUTION

- It may not be possible to use infrared transmission or to transmit properly depending on the other device or on the data. If another application activates during transmission, it will also cause transmission to end.
- Do not point Infrared Port at eyes while transmitting. May affect vision.



■ Receiving Data

1 In Standby,  → "IrDA"

2 "Receive" → "1 Record"/"All Records"

3 Align infrared ports on handset and sending device

Infrared transmission starts, and the data is received.

- When "All Records" is selected, input the same auth code as the sender's →  →  (Accept)

4 "Yes" → "OK"


Data is saved.

- When all contacts in Phone Book are received, confirmation window of additional/overwriting registration appears. Follow onscreen instructions.

■ Sending Data

■ Sending 1 Contact

1 In Standby,  → "IrDA" → "Send"

2 "1 Record" → Select a contact to send → 




3 Align infrared ports on handset and receiving device

Infrared transmission starts, and the contact is sent.

4 "OK"
The contact is sent.

■ Sending All Contacts

1 In Standby,  → "IrDA" → "Send"

2 "All Records" → Enter a password → 
→ Enter the same auth code as the receiver's →  →  (Accept) → "Yes"

3 Align infrared ports on handset and receiving device

Infrared transmission starts, and the contacts are sent.

4 "OK"
All contacts are sent.

■ Sending Profile

1 In Standby,  → "IrDA" → "Send"

2 "My Profile"

3 Align infrared ports on handset and receiving device

Infrared transmission starts, and the profile is sent.

4 "OK"
Your profile is sent.

Disaster


Urgent News

For details, see "Urgent News" (P.4-19).

Registering Safety Information (Disaster Message Board)

Disaster Message Board is a service that you register your safety information when your call may not go through easily due to voice transmission congestion in the event of a large-scale disaster. And if Setup Auto Notify is set, your safety information can be automatically sent by mail to your family or friends that you registered beforehand when you register safety information.



- Registered information can be viewed on mobile phones by SoftBank as well as other carriers' phones. For details on Disaster Message Board, see SoftBank Website.

1 In Standby,  → "Tool" → "Disaster" → "Disaster Message Board"

Disaster Message Board menu appears.

- If Confirmation window appears, follow on-screen instructions.

2 "Register"

3 Check the state () → Select Enter Message field →  → Enter comment →  → "Register"

Safety information is registered.

Deleting Registered Safety Information


1 In Disaster Message Board menu, "Delete" → Select safety information to delete →


 → "Delete"


- In Disaster Message Board menu, "Delete" → "Delete All" → "Yes" to delete all safety information.

Checking Safety Information




1 "Confirm" in Disaster Message Board menu

2 Enter phone number to confirm →  → "Search"

3 Select date and time to confirm →  Safety information appears.

-  (Menu) → "Get the latest" to update safety information.








■ Registering Recipient Address for Automatic Transmission

- 1 "Setup Auto Notify" in Disaster Message Board menu
- 2 Select Recipient Field →  → Enter a recipient → 
 - When entering recipients,  (Search) → "Search Contacts" to refer to recipients from Phone Book.
- 3 "OK"
Registering the recipient is completed.

■ Sending Voice Message (Disaster Voice Messaging)


Disaster Voice Messaging is a service that records and sends a voice message to desired recipients when your call may not go through easily due to voice transmission congestion in the event of a large-scale disaster.

- Not available when you receive no signal or Airplane mode is set. For details on Disaster Voice Messaging, see SoftBank Website.

- 1 In Standby,  → "Tool" → "Disaster" → "Disaster Voice Messaging"
Disaster Voice Messaging window appears.
 - If Confirmation window appears, follow on-screen instructions.
- 2 "Send Voice"
- 3 "Name or phone number" → Enter a recipient →  →  (Next)
 - When entering recipients,  (Search) → "Search Contacts"/"Search History" to refer to recipients from Phone Book or Call Log.
- 4  (Record) → Record a message → 
The voice message is recorded.
- 5 "Send" → "Yes"
Voice message is sent.
 - Select "Play" to confirm record message.
 - To record again, "Record again" → "Yes" →  (Record).

■ Playing Received Voice Message (Disaster Voice Messaging)

When you are notified of received voice message by SMS, "☎" appears in Status Bar. Receive (download) and play a voice message to hear the sender's voice.

1 In Standby,  → "Tool" → "Disaster" → "Disaster Voice Messaging"

Disaster Voice Messaging window appears.







- If Confirmation window appears, follow on-screen instructions.

2 "Listen"


Listen list window appears.

3 Select a message →  → "Yes"

Received voice message window appears, and voice message is played automatically.


- To stop the message, press  (Stop) while playing the message.
- To update the message, press  (Update).
- To change the volume,  (Menu) → "Volume" →  → .
- To change the speaker,  (Menu) → "Speaker" → "On"/"Off."

■ Replying by Voice Message

1  (Reply) in Received voice message window

- Follow onscreen instructions.

■ Deleting Messages

1 In Listen list window, select a message to delete →  (Delete)

2 "Selected" → "Yes"

The message is deleted.

■ To delete multiple messages



"More" → Check message () to delete →  (OK) → "Yes"

Calendar

Viewing Calendar

1 in Standby

Calendar window appears.

- Alternatively, in Standby,  → "Tool" → "Calendar" to show Calendar window.
- Press  (Change) to change Calendar to one week display.

Registering Schedule

1 In Calendar window, (Menu) → "Add" Schedule creation window appears.


2 Enter each item

Item	Description
Subject	Enter Subject.
Start date	Select Start date.
Start time	Select Start time.
End date	Select End date.
End time	Select End time.

Item	Description
All day	Set whether to have schedule All day. Check/Uncheck "All day" (<input checked="" type="checkbox"/>) / (<input type="checkbox"/>)
Repetition	Set whether to register repeatedly.
Notification	Set whether to notify.
Location	Enter Location.
Color	Select Color of schedule.
Detail	Enter Detail.


3 (Set) → "OK" Schedule is registered.

Viewing Schedule List

- 1 In Calendar window,  (Menu) → "List Display" → "Schedule"
Schedule list window appears.



Viewing Birthday List

View contacts whose birthdays are registered to Phone Book as a list.



- 1 In Calendar window,  (Menu) → "List Display" → "Birthday"
Birthday list window appears.

Setting Birthday Reminder



Set to remind you of Birthday at the specified time.

- 1 In Birthday list window,  (Settings) → "Birthday reminder time" → Select time → 
Birthday reminder time is set.



Checking Schedule

- 1 In Calendar window, select a date → 
Schedule list window appears.
- 2 Select schedule → 
Schedule Details window appears.



Editing Schedule

- 1 In Schedule Details window,  (Menu) → "Edit"
- 2 Enter each item →  (Set) → "OK"
Edit is completed.




■ Deleting Schedule

- 1** In Calendar window, select a date → 
→ Select schedule to delete
- 2**  (Menu) → "Delete events"
- 3** "Delete one" → "Yes" → "OK"
Schedule is deleted.



■ To delete multiple schedules

- "Delete multiple" → Check schedules () to delete →  (Delete) → "Yes" → "OK"
- While selecting schedules to delete,  (Menu) → "Check all"/"Uncheck all" to select/cancel all the schedules.

■ Creating Memos




- 1** In Standby,  → "Tool" → "Notepad"
Notepad Entry window appears.
• When Notepad list window appears,  (Menu) → "Add."
- 2** Enter contents →  → "OK"
Notepad is saved.

■ Checking Memos




- 1** In Standby,  → "Tool" → "Notepad"
Notepad list window appears.
- 2** Select a memo →  (Detail)
Notepad Details window appears.

Voice Recorder






Editing Memo

- 1 In Notepad list window, select a memo →  (Edit)
Notepad Entry window appears.
 - Alternatively, in Notepad list window, press  (Edit) to show.
- 2 Edit contents →  → "OK"
Editing the memo is completed.


Deleting Memo

- 1 In Memo list window, select a memo to delete
- 2  (Menu) → "Delete"
- 3 "Delete one" → "Yes" → "OK"
The memo is deleted.
 - **To delete multiple memos**
"Delete multiple" → Check memos () to delete →  (Delete) → "Yes" → "OK"
 - While selecting memos to delete,  (Menu) → "Check all"/"Uncheck all" to select/cancel all the memos.



Recording Voice

- 1 In Standby,  → "Tool" → "Voice Recorder"
Voice Recorder window appears.
- 2 "Record"
- 3  (Record)
Recording starts.
- 4 Record voice →  (Stop) → "OK"
Voice data is saved.
 - Press  (Pause) to pause the recording while recording voice. Press  (Record) to resume recording.
 - Voice Play window appears after recording.



Setting Save Location for Voice

- Change save location for voice to handset storage/SD Card
- 1 In Voice Recorder window,  (Menu) → "Storage" → "Phone"/"SD" → "OK"
Save location is set.



■ Playing Voice

- 1 In Voice Recorder window, "Play"
Voice list window appears.
- 2 Select voice to play →  →  (Play)
Voice Play window appears, and recorded voice is played.
 - Operations while playing voice: (P.9-3)

■ Deleting Voice



- 1 In Voice list window, select voice to delete
- 2  (Menu) → "Delete"
- 3 "Delete one" → "Yes" → "OK"
Voice is deleted.
 - Alternatively, in Voice play window,  (Menu) → "Delete" → "Yes" to delete voice.

■ To delete multiple voices

- "Delete Multiple" → Check voices () to delete →  (Delete) → "Yes" → "OK"
- While selecting voices to delete,  (Menu) → "Check all"/"Uncheck all" to select/cancel all the voices.

■ Viewing Voice Details

Check save date, size, etc.

- 1 In Voice list window, select voice that you show details on →  (Menu) → "Details"
Details on voice appear.
 - Alternatively, in Voice play window,  (Menu) → "Details" to show details.


Calculator

Using Calculator

1 In Standby,  → "Tool" → "Calculator"
Calculator window appears.









2 Enter formula



Calculation result appears.

- Press  (Menu) to copy and paste the result.

Operations for Calculator

Operations for Calculator are as follows:


Calculation	Operation key
+ (Add)	
- (Subtract)	
× (Multiply)	
÷ (Divide)	
= (Equal)	 (=)
c (Clear)	 / CLEAR
AC (All clear)	Long Press 
. (Decimal point)	

Calculation	Operation key
% (Percent)	 (%)
+/- (Symbol change)	

Converter

Convert the unit of length, weight, area, temperature.

Converter Window



Converter Window

- ① Unit type
- ② Unit to convert
- ③ Numerical value to convert
- ④ Converted unit
- ⑤ Converted numerical value

Using Converter

- 1** In Standby, → "Tool" → "Converter"
Converter window appears.
- 2** Select unit type field → → Select unit type to convert →
- 3** Select unit field to convert → →
Select unit to convert → → Select numerical value field to convert → →
Enter numerical value to convert →
- 4** Select converted unit field → →
Select converted unit →
The result appears in converted numerical value field.

あんしんバックアップ (Anshin Backup)

This application saves each data such as Phone Book/Calendar/Call Log/image/music/movie to cloud server or SD Card, or returns data stored in server to handset. It is convenient to transfer data from an old handset to your new handset in the case of handset upgrade/replacement.

- When SD Card is not inserted, data is saved to handset memory. When saving is completed, save location appears.
- Be sure to delete data beforehand in the case of contract change such as the ownership of handset is handed over to a third party. Some data may not be deleted depending on the type of contract change.
- Note that SoftBank Corp. is not liable for any loss/alteration of saved/restored data. And SoftBank Corp. is not liable for any results arising from this application use.
- Specifications may change without notice.

File Name of Saved Data

The file name of saved data is a save date. For example, if a contact file is saved on November 15 in 2017, the name will be "17111500.vcf." When multiple files are saved on the same day, the name will be "17111501.vcf" and the lower 2-digit number will be increased.

Savable Number of Files

Up to 100 files can be saved to server/SD Card, etc. respectively for each Phone Book data/Calendar data/Call Log data/image data/music data/movie data.

When Data Cannot be Saved


When you make settings such as Secret Mode so that you do not allow a third party to view data, some data may not be saved to server.

Restored Data

For data restored by this application, various applications corresponding to each data are available.

■ Login with another SoftBank Account

When saving to data server/restoring from data server, the account that you use can be changed.


- 1 In Standby,  → "Tool" → "あんしんバックアップ (Anshin Backup)"
 - If Confirmation window appears, follow on-screen instructions.
- 2 "その他の機能 (Other Functions)" → "他のアカウントでログイン (Login with another account)"
- 3 Enter the phone number and password → "ログイン (Login)" → "同意する (Agree)"
 - If Confirmation window appears, follow on-screen instructions.
 - Enter SoftBank account to use.

■ Checking Save/Restore History

- 1 In Standby,  → "Tool" → "あんしんバックアップ (Anshin Backup)"
- 2 "その他の機能 (Other Functions)" → "保存履歴 (Save History)"

Save history appears.

■ Checking Help in あんしんバックアップ (Anshin Backup)

- Check application usage, terms of use, application information.
- 1 In Standby,  → "Tool" → "あんしんバックアップ (Anshin Backup)"
 - 2 "その他の機能 (Other Functions)" → "ヘルプ (Help)"

3 "ヘルプ (Help)"/"利用規約 (Terms of use)"/"アプリケーションについて (About applications)"

Each information appears.

■ Saving Data

Save (back up) each data to server/SD Card, etc.

- Since data is saved as available format for other mobile phones, some part of the data may be discarded or altered.
- Call Log/image/music/movie can be saved to only SD Card.

1 In Standby, → "Tool" → "あんしんバックアップ (Anshin Backup)"

- If Confirmation window appears, follow on-screen instructions.

2 "データの保存 (Data Save)"

3 "サーバーにデータを保存 (Save data to server)"/"SD カードにデータを保存 (Save data to SD Card)"

- If Confirmation window appears, follow on-screen instructions.

- When authentication screen appears, enter the phone number and password → "ログイン (Login)" → "同意する (Agree)."

4 Check item () to save →

5 (実行 (OK)) → "OK"

The data is saved.

- To suspend saving, select "キャンセル (Cancel)."
- When data saving is suspended, the data is not saved.

■ Restoring Data

Select data stored to server/SD Card, etc. and restore it to handset memory.

- Call Log/image/music/movie can be stored from only SD Card.
- Some data may not be restored depending on data. And some part of restored data may be discarded or changed.
- The contents of saved data are restored additionally.

1 In Standby, → "Tool" → "あんしんバックアップ (Anshin Backup)"

2 "データの復元 (Data Restore)"

3 "サーバーからデータを復元 (Restore data from server)"/"SD カードからデータを復元 (Restore data from SD Card)"

- If Confirmation window appears, follow on-screen instructions.
- When authentication screen appears, enter the phone number and password → "ログイン (Login)" → "同意する (Agree)."

4 Check item () to restore → Select data to restore →

- If Confirmation window appears, follow on-screen instructions.

5 (実行 (OK)) → "OK"

The data is restored to handset.

- To suspend restoring, select "キャンセル (Cancel)."
- When data restoring is suspended, data is not restored.

■ Saving Data Regularly and Automatically

Save each data to server/SD Card, etc. regularly and automatically.


- Regular save is enabled by default.
- Save all Phone Book data/Calendar data/Call Log data/image data/music data/movie data to server/SD Card, etc.
- Saving data by selecting data one by one or part of data is not available.
- When "サーバーに保存 (Save to server)" is set for save location, only Phone Book data/Calendar data is saved.
- Since data is saved as available format for other mobile phones, some part of data may be discarded or altered.

1 In Standby, → "Tool" → "あんしんバックアップ (Anshin Backup)"

- If Confirmation window appears, follow on-screen instructions.

2 "定期保存 (Regular save)"


- If Confirmation window appears, follow on-screen instructions.

- 3** Set 更新頻度 (Update frequency)/ 日付 (Date)/ 保存先 (Save location)/ 対象 (Subject) →  (保存 (Save))

Regular save is set.





Reloading Phone Book Data Saved to Server in Case of Handset Upgrade/Replacement

You can transfer data stored in the S!Phone Book backup server to Phone Book of your new handset if you previously used 3G mobile phone and S!Phone Book backup service.

- 1** In Standby,  → "Tool" → "あんしんバックアップ (Anshin Backup)"
- If Confirmation window appears, follow on-screen instructions.
- 2** "電話帳の移行 (Data transfer of address book)"
- 3** "OK" → "Yes"
- Loading the data is completed.
- If Confirmation window appears, follow on-screen instructions.
 - When authentication screen appears, enter the phone number and password → "ログイン (Login)" → "同意する (Agree)."

Deleting Saved Data

Delete data saved to server/SD Card, etc. Note that deleted data cannot be restored.

- 1** In Standby,  → "Tool" → "あんしんバックアップ (Anshin Backup)"
- 2** "その他の機能 (Other Functions)"
- 3** "保存データの削除 (Delete saved data)"
- 4** "サーバーのデータを削除 (Delete data in server)"/"SD カードのデータを削除 (Delete data in SD Card)"
- If Confirmation window appears, follow on-screen instructions.
 - When authentication screen appears, enter the phone number and password → "ログイン (Login)" → "同意する (Agree)."
- 5** Check files () to delete →  →  (Delete)
- While selecting files to delete,  (Menu) → "Check all"/"Uncheck all" to select/cancel all the files.

Notification List

6 "OK" → "OK"

The data is deleted.

- To suspend deleting, select "キャンセル (Cancel)."

Check new notifications (incoming call, mails, etc.) or notifications from each function.


7 In Standby, → "Tool" → "Notification List"

Notification List window appears.

- Selecting notification activates corresponding function.

Application

Check the list of installed applications in handset.

1 In Standby,  → "Tool" → "Application"

Application list window appears.

- Select application →  to activate application.